

RELIX Reset after changing batteries

- For Model
4336010 for indicator 1/100mm resolution
To Reset the device make the following procedure
Insert the battery then press key mm/inch and OI(red) contemporaneously for more as 3 sec.
the display shows now 01 00 or similar now press key OI(red) to increase or mm/inch key to decrease the last to numbers to 03
now press the OI(red) key for more as 3 sec. The display should change to 03—06 and when you release the key the display should show 0.00 and normal work.
- For Model
4336030 for indicator 1/1000mm resolution
To Reset the device make the following procedure
Insert the battery then press key mm/inch and OI(red) contemporaneously for more as 3 sec.
the display shows now 01 00 or similar now press key OI(red) to increase or mm/inch key to decrease the last to numbers to 05
now press the OI(red) key for more as 3 sec. The display should change to 05—06 and when you release the key the display should show 0.00 and normal work.